

Relay switching module with reader and keyboard K226+G16, 10-30V DC

Product codes:

Reference: AM1639

EAN13: -

UPC: 85364190

Product features:

Voltage: 10-30 V DC

Waterproof grade: IP22



Product attributes:

Product description:

The K226 + G16 kit is an advanced access system combining a control board and an external fingerprint reader. By connecting with the G16, it offers secure and convenient control of electronic locks and other devices. It allows the management of multiple administrators, users and one-time passwords and provides up to four relay control modes. This kit is an ideal choice for installations requiring flexible and reliable security.

Technical specifications

- Power supply: DC 10-30V
 - Standby consumption: 6 mA (at 12 V)
 - Output: relay (max. current 10 A)
 - Adjustable relay switching time: 0.5 s - 30 minutes
 - Fingerprint capacity:
 - Administrator: up to 40 fingerprints
 - User: up to 60 fingerprints (2 databases of 30 each)
 - Password capacity:
 - Administrator: up to 5 groups
 - User: up to 5 groups (3-9 digits)
 - Disposable: up to 5 groups
-

- Control: SET button, fingerprint, password
- G16 reader: external fingerprint sensor with LED indication

Functions and features

- Combination of biometric identification and password access
- Simple user registration directly via the G16 reader
- Support for administrator and user accounts
- Option for one-time passwords for temporary access
- Four relay control modes - time, momentary, latching without memory, latching with memory
- Possibility to set the relay to switch on for up to 30 minutes
- Status indication using LED reader G16

Relay modes

- **Mode 1 (time):** The relay switches on for the set time (0.5 s - 30 minutes).
- **Mode 2 (momentary):** The relay remains closed only as long as the finger is applied.
- **Mode 3 (self-latching without memory):** First finger touch → relay closes, second touch → relay closes. The relay state is not saved after power is disconnected.
- **Mode 4 (latching with memory):** Same as mode 3, but the relay remembers the state even after a power failure.

Ideal for

- Electronic door locks
- Access systems for homes and businesses
- Control of relays and electrical appliances
- Security systems requiring a higher level of protection

Package contents

- Control board K226
- G16 Fingerprint Reader
- Connectors for wiring
- User manual (EN)

Why choose this set?

- Combination of G16 reader and K226 control board for maximum flexibility
 - Support for multiple administrators, users and one-time passwords
 - Four relay control modes adaptable to specific applications
 - Easy installation and intuitive management
 - Reliable LED signaling for clear operation
-

Instructions for use

- **1. First start:** Hold down the SET button for 5-6 seconds to restore factory settings.
- **2. Administrator registration:** Short press SET, the blue LED on G16 flashes quickly. Place your finger repeatedly until you hear a musical tone. Up to 40 fingerprints can be stored.
- **3. User registration:** Log in with the administrator fingerprint or password. Select the database (1 or 2) and attach the user's finger. Each database allows 30 fingerprints.
- **4. Password settings:** The administrator can add up to 5 passwords for both users and administrators (3-9 digits). 5 one-time passwords can also be set.
- **5. Relay settings:** Log in as administrator and select mode (1-4). For time mode, set the switching time (0.5 s - 30 minutes).
- **6. Usage:** Access is possible by placing a registered finger on the G16, entering a password or one-time password.

Product gallery:

